

How-to:

Automatic tab creation



How-to: Automatic tab creation

Feature overview

The Auto Tabs feature creates tab sheets, places them in the right location and populates the tab ear content automatically by using bookmark links from PDF documents.

Auto Tabs is especially valuable for long documents that require well-defined chapters or sections, such as training manuals, reports or course packs.

Objectives of exercise

- Convert PDF bookmarks into tabs.



Additional resources

For additional software downloads, training resources and more, go to [Fiery Online Resources](#).

Before you begin

- Open Fiery Command WorkStation® 6 or later and connect to a Fiery server running Fiery FS350/FS350 Pro that supports Fiery JobMaster.
 - For the updated list of supported printers, go to www.efi.com/fieryjobmaster.
- To request the free 30-day trial for Fiery JobMaster, go to: <http://fiery.efi.com/jobmaster/freetrial30>.
- Activate the Fiery JobMaster license on the computer running Command WorkStation.
- Place the file, **MnM_Catalog_bookmarks_SAMPLE_LTR.pdf** or **MnM_Catalog_bookmarks_SAMPLE_A4.pdf**, in the Fiery server HELD queue. Drag the file to the Command WorkStation Held list or use the Command WorkStation Import menu option.
- Ensure the printer and Fiery server have been calibrated before printing any output.

How-to: Automatic tab creation



Convert PDF bookmarks using Auto Tabs

1. Select the **MnM_Catalog_bookmarks_SAMPLE_LTR.pdf** or **MnM_Catalog_bookmarks_SAMPLE_A4.pdf** file in the Command WorkStation Held list. Then right-click and select **JobMaster**.
2. In the JobMaster window, click **Actions > Auto Tabs > Convert Bookmarks to Tabs**.
3. In the Edit Tab window, modify the tab text and background color.
4. Change the font to **Arial** and the font size to **10**.
5. In the Tab Set Options area, click the **Apply styles to all** button. Clear all the option check boxes except **Text styles** and click **Apply**. This will apply the same font and font size to all tabs.
6. To add a background color to the tab text field, click . When the icon changes to select the Background Color.
7. For this example, specify the RGB values for each tab section color. Define the background color according to the chart information below.


Tab Position	Tab Text	Background Color
Tab 1/5	Cooking tools	41,23,107
Tab 2/5	Spices	156, 48,26
Tab 3/5	Cookware	46, 126, 226
Tab 4/5	Coffee	132,51,43
Tab 5/5	Tea	138,141,75

Navigation tip: Use keyboard shortcuts to quickly jump between tabs in the Edit Tab window. Use command-right (or left) arrow on a Mac and Ctrl-right (or left) arrow in Windows®.

*Background Color: Create a color palette for frequently used colors. Just click a color box under Custom colors and then click **Add to Custom Colors** to add each new color to the Custom colors as you define each one. It saves time for future jobs.*

8. In the Tab Set Options area, select **5 Bank tab** in Media Preset. If no media presets have been created yet, then click **Edit** next to Media Preset.

How-to: Automatic tab creation



9. In the Tab Media dialog box, verify the Number of tabs in a set is **5**.
10. For this example, use the default selection **Forward** for Tab sequence.

Select the tab sequence that is appropriate for the tab stock and media tray you are using to print tabs.

11. Specify the Output Tray to kick out unused tabs. (This option will vary with printer).
12. Continue to assign any additional settings, including media, tray or Paper Catalog.
13. Click the **disk** icon next to Media Preset after you have completed all the settings you want.
14. Name your preset **5 Bank Tab** and click **OK**.
15. The selected media preset will display **5 Bank Tab**.

Media Presets will save the tab template setup for use in future jobs. You can save multiple presets for various tab media.

16. Click **OK** to exit the Edit Tab window.
17. In the Settings pane, specify any additional settings. For this example, set the Duplex option to **Top-Top**.
18. Click **File > Save**.
19. **Save** the job as default setting and click **OK**.
20. Click **File > Exit** to close JobMaster. Or click the red **X** in the corner.
21. The job is ready for printing.

EFI fuels success.

We develop breakthrough technologies for the manufacturing of signage, packaging, textiles, ceramic tiles, and personalized documents, with a wide range of printers, inks, digital front ends, and a comprehensive business and production workflow suite that transforms and streamlines the entire production process, increasing your competitiveness and boosting productivity. Visit www.efi.com or call 650-357-3500 for more information.



Nothing herein should be construed as a warranty in addition to the express warranty statement provided with EFI products and services.

The APPS logo, AutoCal, Auto-Count, Balance, BESTColor, BioVu, BioWare, ColorPASS, Colorproof, ColorWise, Command WorkStation, CopyNet, Cretachrom, Cretaprint, the Cretaprint logo, Cretaprinter, Cretaroller, Digital StoreFront, DirectSmile, DocBuilder, DocBuilder Pro, DockNet, DocStream, DSFdesign Studio, Dynamic Wedge, EDOX, EFI, the EFI logo, Electronics For Imaging, Entrac, EPCount, EPPhoto, EPRegister, EPStatus, Estimate, ExpressPay, FabriVU, Fast-4, Fiery, the Fiery logo, Fiery Driven, the Fiery Driven logo, Fiery JobFlow, Fiery JobMaster, Fiery Link, Fiery Navigator, Fiery Prints, the Fiery Prints logo, Fiery Spark, FreeForm, Hagen, Inkintensity, Inkware, LapNet, Logic, Metrix, MicroPress, MiniNet, Monarch, OneFlow, Pace, Pecas, Pecas Vision, PhotoXposure, PressVu, Printcafe, PrinterSite, PrintFlow, PrintMe, the PrintMe logo, PrintSmith, PrintSmith Site, PrintStream, Print to Win, Prograph, PSI, PSI Flexo, Radius, Remoteproof, RIPChips, RIP-While-Print, Screenproof, SendMe, Sincolor, Splash, Spot-On, TrackNet, UltraPress, UltraTex, UltraVu, UV Series 50, VisualCal, VUTEK, the VUTEK logo, and WebTools are trademarks of Electronics For Imaging, Inc. and/or its wholly owned subsidiaries in the U.S. and/or certain other countries. All other terms and product names may be trademarks or registered trademarks of their respective owners, and are hereby acknowledged.